

Print Distribution Lists

This chapter covers the following topics:

- Description
 - Procedure
 - Batch Example
-

Description

Program

B07100

Function

Print a list of all distribution lists in which the specified member(s) is defined.

Online Input Screen

11:53	* * * C o n - n e c t 3.4.1 * * *	9.Dec.03
Cabinet LS	Print Distribution Lists with Specific Member	B07100
From cabinet _____ to cabinet _____		
('*' for all cabinets)		
Member ID _____		
Member name _____		
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---		
Menu Quit		
Complete the information above and press ENTER to continue		

Utility Parameters

Parameter	Format	Description
From cabinet	A8	
to cabinet	A8	Optional
Member ID	A16	Optional
Member name	A20	Optional

Procedure

Only cabinet administrators can print a list of distribution lists from cabinets other than their own. Users can print only a list of distribution lists from their own cabinet.

Either member ID or member name must be specified, but not both.

To print all distribution lists that contain a specific member ID, enter the ID in parameter Member-ID. If a member ID with an asterisk (e.g. SA*) is specified, then all member IDs that begin with the characters are printed. An asterisk cannot be specified without one or more characters.

To print all distribution lists that contain users with a specific name, enter the last name in parameter Member-name. If one or more characters are specified with an asterisk (e.g. Sm*), then all members whose last name begin with those characters are printed. An asterisk cannot be specified without one or more characters.

The resulting printout contains the name of the distribution list in which the specified member is defined, the cabinet, member ID, member name and type of member.

Batch Example

Print a list of distribution lists from all cabinets that contain member IDs beginning with the letter A. This would be coded as follows:

```
LOGON SYSCNT2B
MENU
B07100 *, ,A*
FIN
```

Print a list of distribution lists from all cabinets which contain users with the last name Landrey. This would be coded as follows:

```
LOGON SYSCNT2B
MENU
B07100 *, , ,Landrey
FIN
```